



PORTABLE GENERATOR



1000W* of UNBEATABLE POWER



- Elite Class 98cc OHV Engine with Cast Iron Bore
- 8 Liter Fuel Tank with Fuel Gauge
- Convenient Control Panel Includes:
 - Covered 230V AC Socket
 - 12V DC Socket
 - Voltmeter
- Premium Automatic Voltage Regulator – AVR
- 1 Year Limited Warranty

100% COPPER WIRE



Recreation







Home



Business



PORTABLE GENERATOR

GENERATOR				
Model #	SL1200(038031)	SL1200(030610)	SL1500(038032)	SL1500(030611)
Receptacle				
Type	Copper wiring/single phase		Copper wiring/single phase	
Rated Voltage	230V		230V	
Frequency	50Hz		60Hz	
Rated Output	900W		1000W	
Rated AC	3.92A		4.35A	
Max. Output	1000W*		1200W*	
Max. AC	4.35A		5.22A	
DC Output	12V/8.3A		12V/8.3A	
Voltage Regulator	AVR		AVR	
Material of Bore	Cast Iron Bore		Cast Iron Bore	
Displacement	98CC		98CC	
Starting System	Recoil		Recoil	
L×W×H	456X365X406mm		456X365X406mm	
Dry Weight	28kg		28kg	
Fuel Tank Capacity(full)	8L		8L	
Operating Hours	11.6Hrs		8.4Hrs	
Noise Level(at 7m)	76dB(A)		79dB(A)	
Circuit Breaker System	Yes		Yes	
Fuel Level Gauge	Yes		Yes	
Voltage Meter	Yes		Yes	
AC Plug	Yes		Yes	
DC Charging Cord	Yes		Yes	

* This generator is rated in accordance with ISO 8528 G1

Trusted Power Equipment Solutions For Over 100 Years

- Providing Power to Millions of People to Get The Job Done
- World Class Engineering and Product Development
- Global Services & Support Network



THE POWER WITHIN™